

# A4X60 / A4X120

## Four channel amplifier



### A4X range

The **A4X60 /A4X120** multi zone power amplifier is designed for public address setups requiring up to 4 different simultaneous playback zones.

An extremely versatile 4 zone / 4 source power amplifier is like having four separate power amplifiers in one chassis. Each power amplifier module features a balanced barrier strip input connection and a separate volume control. With a choice of 100 V, 70 V and 8 Ohm speaker outputs for each power amplifier, it's perfect extension for a demanding background music, public address or advertising setups in schools, shops, restaurants and small hotels.

### TECHNICAL SPECIFICATIONS

*unit: mm*

	<b>A4X60</b>	<b>A4X120</b>
Output power	<b>Max</b> 4×90 W <b>Rated</b> 4×60 W	<b>Max</b> 4×180 W <b>Rated</b> 4×120 W
AC power consumption	640 W	1280 W
DC power consumption	360 W	720 W
Outputs	<b>Speaker</b> — 8 Ω, 70 V, 100 V;	
Inputs	<b>Line input</b> 1V, 10 kΩ (balanced)	
Frequency response	50 Hz–20 kHz	
THD	Less than 1 % at 1 kHz, rated power	
Signal/noise ratio	86 dB below rated power	
Controls	Input gain control (rear panel)	
Indicators	Power indicator (LED), output level indicator (6 LEDs)	
Power supply	<b>AC</b> 230 V, 50 Hz ±10%; <b>DC</b> 24 V (max 10% deviation)	
Weight	21 kg	24 kg
Dimensions	132 mm × 425 mm × 420 mm	
Color	Black	
Mounting options	Table top or 19" rack mountable	